

IP65 LED VANDAL PROOF BATTEN LIGHT INSTRUCTION MANUAL



INSTALLATION



CAUTION: RISK OF ELECTRIC SHOCK!

WORK MUST BE CARRIED OUT BY AN ELECTRICIAN OR COMPETENT PERSON. IF IN DOUBT, SEEK PROFESSIONAL ADVICE.



Isolate power to circuit of which light will be installed

Separate components, removing the diffuser and LED tray from the base.

EMERGENCY VERSION
Switched Live
Permanent Live
Earth
Neutral

STANDARD VERSION
Switched Live
Earth
Neutral

Insert cable through entry hole and connect to push fit connector block as above. Do not drill holes on any part of the fitting.

Re-fit cable tray to base. Attach clips to base and latch onto diffuser.

Screw the provided mounting brackets to ceiling/wall, push light fitting up and attach to brackets. (For chain mounting see below)

After sufficient testing of installation, power up supply and test further.

Voltage	AC110-240V
Frequency	50Hz
Wattage	40W
Lumens	4200Lm
Power Factor	>0.6
CRI	>80
Lifespan	25000 hours
Installation	Surface
IP Rating	IP65
Dimmable	No
Beam Angle	180°
Colour Temp	4000K

Fix expansion screws onto ceiling (not included), secure chain (not included) onto the mounting brackets.

EMERGENCY VERSION
In the event of loss of power to the fitting, the emergency battery backup will start, lasting 3 hours

MAINTENANCE

If required, it is possible to clean the fitting with a dry cloth, be sure not to loosen any components whilst cleaning. If essential to remove diffuser to clean, isolate power first.

Do not attempt to modify this light fitting in anyway, as this may cause damage to the item or potential harm to person(s) using it.

The light source will last 30,000 hours, once the light source dies, it will be required to replace the entire unit. Please dispose of the old unit in a responsible manner and recycle where possible.

Replacement fittings can be purchased at www.sparkLED.co.uk

For further advice/enquires, please visit www.sparkLED.co.uk

THE LIGHT SOURCE IN THE TRAY CANNOT BE REPLACED. PLEASE DISPOSE OF RESPONSIBLY AND REPLACE THE LED TRAY.

DISPOSAL

Correct Disposal of This Product (Waste Electrical & Electronic Equipment) (Applicable in the European Union and other European countries with separate collection systems). This marking shown on the product or its literature, indicates that it should not be disposed with other household wastes at the end of its working life. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate this from other types of wastes and recycle it responsibly to promote the sustainable reuse of material resources. Household users should contact either the retailer where they purchased this product, or their local government office, for details of where and how they can take this item for environmentally safe recycling. This product should not be mixed with other commercial wastes for disposal.

FURTHER MAINTENANCE

The fittings are maintenance-free, so never open them. The guarantee becomes void when you open the appliance. Only clean the outside of the devices with a soft, dry cloth or a brush. Prior to cleaning, remove the devices from all voltage sources. Do not use any carboxylic cleaning agents or petrol, alcohol or similar. These damage the surfaces of the devices. Besides, the vapours are hazardous to your health and explosive. Do not use any sharp-edged tools, screw drivers, metal brushes or similar for cleaning.

GENERAL SAFETY

Keep all parts out of the reach of children. Avoid dropping or shocks; this may damage the electronic circuits. Repairs or opening of this item may only be done by an authorized repairer. For your safety, always switch off the power supply before changing lamps, adjusting spotlight, heads or cleaning

HIGH VOLTAGE

All electrical connections and connection cables must comply with the appropriate rules and match the operating instructions. The fitting must be correctly installed if it is to operate reliably. These instructions and the user guide must therefore be studied carefully. The electrical supply must be switched off at the consumer unit, preferably by means of a switch in the distribution box, before any installation, maintenance or repair work is undertaken. Exterior components must not be installed during rain. Take account of the minimal separation distance from other objects and the room required around the fitting. If in any doubt consult a professional, taking local installation requirements into account. Some countries stipulate that lighting may be installed only by registered installers

WARRANTY

This product comes with a 2-year warranty (not including lamps). If you have any concerns or questions do not hesitate to contact us.

